


# YES1-32 ~ 125N

## AUTOMATIC TRANSFER SWITCH



### Product Type



Name	Content		
Enterprise code	Shanghai Yuhuang Electric Co.,Ltd		
Product category	PC Class Automatic Transfer Switch		
Design code	1		
Current rank	<b>Product code</b>	<b>Current rank</b>	
	N	32A,63A,125A	
Product code	<b>Product code</b>	<b>Working current</b>	<b>Features</b>
	N	16A~125A	Split type , 2 positions, terminal wiring type block connect
Pole	3P ,4P		
Rated current	16A~125A		
Working mode	R=Self-input and self-recover B=II circuit first F: Utility- Generator T=Communication		

### Technical parameter

Model	Type	YES1-32N			YES1-63N			YES1-125N		
		2P	3P	4P	2P	3P	4P	2P	3P	4P
Rated current (A)		16,20,25,32			40,50,63			80,100,125		
Rated control current (A)					5					
Rated short circuit current (kA)					10					
The rated impulse withstand voltage (kV)					8					
Usingzation Category					AC-33B					
Service life	Mechanical				20000					
	Electric				6000					
Pole		2P	3P	4P	2P	3P	4P	2P	3P	4P
Operating cycle(s/time)					10					